

Design by: Masiero Lab

### MARIA TERESA VE919



#### MT



#### MT Traditional version

<b>LIGHTING</b>	Traditional E12 lightbulbs
<b>SIZE</b>	With lampshades, overall diameter is 5 cm (2") larger than specified
<b>FRAME</b>	<b>MT</b> Chrome or gold plated metal covered with transparent glass
<b>PENDANTS</b>	<b>MT</b> Transparent glass or crystal


#### RW/DW



#### RW RGB-W Led version DW Dynamic White Led version

<b>LIGHTING</b>	WHITE LED sources CRI>90 <b>RGB-W</b> each light 330 Nominal lm at 3000K <b>DW</b> each light 490 Nominal lm at 4700K
<b>SIZE</b>	Same size as MT
<b>FRAME</b>	Chrome or gold plated metal covered with transparent glass
<b>PENDANTS</b>	Transparent glass or crystal

### VE 919/PL10



TECHNICAL INFORMATIONS	
<b>Ø</b>	90 cm / 35.43"
<b>H</b>	35 cm / 13.77"
<b>W</b>	34 kg / 74.95 lb


LIGHTING SYSTEM
10×E12×40 W max (not included). Triac Dimmable

VERSION
<b>VE 919/PL10 MT</b>

10×LED source -40 W tot Control system: DMX On request Radio Control and Masiero Smart Light App only for RW version.
---

<b>VE 919/PL10 RW/DW</b>
------------------------------

#### MT TRADITIONAL




G04 Shiny chrome



G03 Shiny gold


#### MT DYNAMIC WHITE



#### MT RGB - W - LED



### VE 919/PL12



TECHNICAL INFORMATIONS	
<b>Ø</b>	105 cm / 41.33"
<b>H</b>	35 cm / 13.77"
<b>W</b>	44 kg / 97 lb


LIGHTING SYSTEM
12×E12×40 W max (not included). Triac Dimmable

VERSION
<b>VE 919/PL12 MT</b>

12×LED source -48 W tot Control system: DMX On request Radio Control and Masiero Smart Light App only for RW version.
---

<b>VE 919/PL12 RW/DW</b>
------------------------------

### VE 919/PL20



TECHNICAL INFORMATIONS	
<b>Ø</b>	130 cm / 51.18"
<b>H</b>	45 cm / 17.71"
<b>W</b>	80 kg / 176.36 lb

LIGHTING SYSTEM
20×E12×40 W max (not included). Triac Dimmable

VERSION
<b>VE 919/PL20 MT</b>

20×LED source -80 W tot Control system: DMX On request Radio Control and Masiero Smart Light App only for RW version.
---

<b>VE 919/PL20 RW/DW</b>
------------------------------